



W = Width, D = Depth, H = Height



Inverter 1200W 12V

Item number: see below

Inverter 1200W 12V

Our inverters belong to a series of high quality inverters. They are dimensioned to bear heavy use and give the utmost power. All inverters can be operated from a remote panel connected to the inverter. The inverters deliver pure sine.

DEFA AS is conforming to the requirements of both ISO 9001:2008, ISO 14001:2004 and OHSAS 18001:2007. In addition to this, our engine heaters and cables are conforming to the requirements of ISO/TS 16949:2002.

Installation

Equipment damage and possible injuries may result from an incomplete understanding of the installation and operation of the charger. If you are unfamiliar with electrical systems; consult us, a dealer or a licensed electrician.

Read the mounting and user guide carefully.

Use

The inverter should be used indoor and not be exposed to rain or moisture. Make sure the connected battery is fully charged. Switch off the inverter when it's not in use. The inverters are equipped with protection against wrong usage or connection and a buzzer will sound in some situations. Never open the inverter yourself, repairs should be carried out by qualified personal using original spare parts to avoid personal and property damage.

Maintenance

The inverter is maintenance free.

Technical specifications

Input voltage [VDC]	10-16
Constant output power [W]	1200
Peak power (2s) [W]	2400
Output voltage, pure sine wave [VAC]	220~240
No load, power consumption [A]	< 1,7
Eco mode, Power consumption [A]	< 0,6
Auto shut off, high voltage [V]	16,5 (± 0,5)
Alarm for low voltage [V]	10,8 (± 0,5)
Auto shut off, low voltage [V]	10,0 (± 0,5)
Input Fuse [A]	40 (5)
Operating temperature [°C]	-30~+60
H/W/D [mm]	360*225*92,5
IP rate [IP]	20
Weight (w/o cables) [Gr]	4500
Approvals	61558-2-16:2009 AMD 1:2013, 61558- 1:2005 AMD1:2009 E13*10R05/01*15196*00

Item no.	
709090	With transfer switch
709091	Without transfer switch